

LFI3751 5A Digital Temperature Control Instrument

- Drive ± 5 A of TEC or RH current
- Digital PID Improves Stability for RTDs
- Addressable RS-232 or USB
- Supports Thermistors, RTDs, IC sensors
- Free Labview drivers
- Linear Stability: 0.001°C
- PID Autotune
- Autoranging sensor bias currents
- Heat and cool current limits
- High and low temperature limits



Power Supply: 115 / 230 VAC 60/50 Hz

Temperature Control Output Current: up to ± 5 A

Temperature Stability: 0.001°C (10 k Ω thermistor at 25°C) over one hour

Stability across ambient: 0.001°C (10 k Ω thermistor at 25°C) over an hour ---- Ideal for scanning ap

Setpoint Resolution: 12 bit D to A

Features:

- Digital version provides better set point resolution and stability with low resolution sensors such as R
- Digital version also offers improved overshoot suppression, 50% faster settling times, and faster calib
- High and Low Temperature Limits
- Heat and Cool Current Limits
- Digital PID controller with Autotune minimizes overshoot and time to temperature
- RS232 or USB interface
- Free Labview drivers or Benchlink software
- Easy sensor calibration
- Compatible with multiple sensors - especially for low resolution RTDs
- Autoranging sensor bias current optimizes sensor feedback voltage
- Can operate with unipolar current for Resistive Heaters

The **LFI3751** with Autotune PID is a high performance temperature control instrument. Drive up to ± 5 A to either thermoelectrics (TECs) or resistive heaters (RH) with up to 8 V compliance. This instrument operates from AC (115 / 230, 50 or 60Hz). Expect stability as good as 0.001°C with thermistors. Even across ambient, this PID controller maintains precision temperature.

From the front panel, adjust temperature limits, current limits, setpoint, PID control values, sensor calibration data, and enable or disable output current. The 4-digit display shows actual or setpoint temperature or resistance, output current and voltage.

This instrument offers unique features. Autotune PID is a sophisticated algorithm for optimizing the PID control parameters to your load. With the touch of a button, the LFI3751 automatically optimizes control settings for most thermal loads, reducing overshoot or improving temperature stability. Autoranging sensor bias currents keep your sensor voltage in the optimal range for maximum signal to noise ratio. It comes with Addressable RS232 and USB control is available with an adapter cable: WCB404. Free Labview drivers simplify computer control. Benchlinksoftware simulates the front panel control from your PC. (NOTE: The Benchlink Installer is not compatible with 64-bit operating systems. A work-around for Benchlink install is available. Contact Tech Support for details if your application uses the Windows 64-bit OS and Benchlink front panel emulation control.)

Sensor calibration is easy with a reference right on the front panel. For example, to calibrate your thermistor, simply enter three data points from the Resistance vs. Temperature curve. The **LFI3751** calculates the Steinhart-Hart coefficients and displays either actual temperature or sensor resistance. Also view Thermoelectric current and voltage and limit current settings.

The LFI3751 Digital option provides better set point resolution and stability with low resolution sensors such as RTDs. This option also offers improved overshoot suppression, 50% faster settling times, and faster calibration. An Analog control model is available: LFI3751 Analog

Wavelength also offers temperature control instruments with higher current and voltage capacity [\[TC5LAB \(5A, 15V\)\]](#) or [\[TC10LAB \(10A, 15V\)\]](#), a touchscreen interface, IntelliTune PID control optimization, and better stability.

Free, effective, and responsive technical support is available to simplify integration of Wavelength products into your OEM design. Standard product can be easily modified to meet your application