



**Wire assignment**

No.	Symbol	I/O	Function	No.	Symbol	I/O	Function
1	GND2		Ground 2	2	+5V2		Power Supply 2
3	GND2		Ground 2	4	+5V2		Power Supply 2
5	LDT-MON	O	LD Temperature Monitor	6	ASE-MON	O	ASE Output Monitor
7	NC			8	LDC-MON	O	LD Current Monitor
9	LDC-ALM	O	LD Current Alarm	10	ASE -ALM	O	ASE Output Alarm
11	NC			12	LDSD	I	LD Shutdown
13	CT-MON *	O	Case Temp. Monitor	14	NC		
15	TXD		LD drv. Transmit Data (PC RXD)	16	RXD		LD drv. Receive Data (PC TXD)
17	+5V1		Power Supply 1	18	GND1		Ground 1
19	+5V1		Power Supply 1	20	GND1		Ground 1

\*: オプション機能 (非搭載製品の場合"NC"となります)

- (1)各ワイヤーは、øBrown-#01øi øBlack-#20ø で対応しております。
- (2)各種アナログモニタ時のグラウンドには、øGND1ø をご使用ください。
- (3)各種アラームは、正常時: CMOS high level (>4.5V)、異常時: CMOS low level (<0.5V) が出力されます。
- (4)LD Shutdown 機能使用時は、øLDSDøへ CMOS Low level (または Ground level)を入力してください。  
解除時は、CMOS High level を入力するか、オープンとして下さい。励起 LD が自動復帰します。